

## NSLS OHSAS Job Risk Assessment

The only official copy of this file is the one on-line in the NSLS ESH website. Before using a printed copy, verify that it is the most current version by checking the document issue date on the NSLS ESH website.

<b>Name(s) of Risk Team Members:</b> J. Aloï, B. Best, J. Burke, B. Clay	<b>Point Value → Parameter ↓</b>	1	2	3	4	5
<b>Job Title:</b> <span style="color: blue;">Work On Electrical Equipment in Zero Energy State</span>  <b>Job Number or Job Identifier:</b> <span style="color: blue;">LS-JRA-0002</span>	<b>Frequency (B)</b>	≤once/year	≤once/month	≤once/week	≤once/shift	>once/shift
<b>Job Description:</b> Perform maintenance, servicing or repair of de-energized electrical equipment.	<b>Severity (C)</b>	First Aid Only	Medical Treatment	Lost Time	Partial Disability	Death or Permanent Disability
Training and Procedure List (Optional):	<b>Likelihood (D)</b>	Extremely Unlikely <<1x/20yrs	Unlikely 1x/10-20yrs	Possible >1x/10-20yrs	Probable 1x/yr	Multiple >1x/yr
Approved by: <b>W. R. Casey</b> Date: <b>10/10/05</b> Rev. #: 1 <span style="color: blue;">Revision Log</span>	<b>Stressors (if applicable, please list all):</b>		<b>Reason for Revision (if applicable):</b>		<b>Comments:</b>	

		Before Controls							After Initial Controls						After Additional Controls					
Job Step / Task	Hazard	Stressors Y/N	# of People A	Frequency B	Severity C	Likelihood D	Risk* AxBxCxD	Initial Controls	# of People A	Frequency B	Severity C	Likelihood D	Risk* AxBxCxD	Control(s) Added to Reduce Risk	# of People A	Frequency B	Severity C	Likelihood D	Risk* AxBxCxD	% Risk Reduction
Verify equipment is de-energized	Electrocution, electrical shock, arc flash, reflex injury	-	-	-	-	-	-	See <b>LS-JRA-0005</b> Lockout-Tagout	-	-	-	-	-							
Assembly, disassembly, and cleaning of components or	Cuts or scrapes	N	1	4	2	3	24	Proper tools in good condition, gloves	1	4	1	2	8							
	Striking hand or arm against a surface	N	1	4	2	3	24	Proper tools in good condition, gloves	1	4	1	2	8							

## NSLS OHSAS Job Risk Assessment

The only official copy of this file is the one on-line in the NSLS ESH website. Before using a printed copy, verify that it is the most current version by checking the document issue date on the NSLS ESH website.

Job Step / Task	Hazard	Before Controls						Initial Controls	After Initial Controls					Control(s) Added to Reduce Risk	After Additional Controls					
		Stressors Y/N	# of People A	Frequency B	Severity C	Likelihood D	Risk* AxBxCxD		# of People A	Frequency B	Severity C	Likelihood D	Risk* AxBxCxD		# of People A	Frequency B	Severity C	Likelihood D	Risk* AxBxCxD	% Risk Reduction
equipment	Strain injuries	N	1	4	3	3	36	Proper tools in good condition, proper body position	1	4	2	2	16							
	Struck by an object	N	1	4	2	3	24	Use of PPE (hard hat, safety shoes, safety glasses	1	4	2	2	16							
	Intense visual acuity	N	1	4	1	3	12	Good lighting, frequent breaks, use of magnifying equipment	1	4	1	2	8							
	Working in cramped locations	N	1	2	3	4	24	Move cautiously	1	2	3	4	24							
Soldering electrical components	Contact with temperature extremes (burns)	N	1	3	2	3	18	Safety glasses, equipment design and condition.	1	3	2	2	12							
	Exposure to toxic gases and fumes	N	1	3	1	4	12	Type of solder used (e.g. lead free), limit amount of solder to quantities necessary for proper solder joints.	1	3	1	3	9							
	Fire	N	1	3	3	2	18	Properly designed soldering tool storage stands, Building fire detection and protection systems.	1	3	3	1	9							
Cleaning components and equipment using chemicals	Chemical exposure	-	-	-	-	-	-	See <b>LS-JRA-0021</b> Routine Chemical Use	-	-	-	-	-							
Testing of electronic assembly's	Electrocution, electrical shock, arc flash, reflex injury	-	-	-	-	-	-	See <b>LS-JRA-0003</b> ; Troubleshooting energized electrical	-	-	-	-	-							

## NSLS OHSAS Job Risk Assessment

The only official copy of this file is the one on-line in the NSLS ESH website. Before using a printed copy, verify that it is the most current version by checking the document issue date on the NSLS ESH website.

		Before Controls							After Initial Controls						After Additional Controls										
Job Step / Task	Hazard	Stressors Y/N	# of People A	Frequency B	Severity C	Likelihood D	Risk* AxBxCxD	Initial Controls	# of People A	Frequency B	Severity C	Likelihood D	Risk* AxBxCxD	Control(s) Added to Reduce Risk	# of People A	Frequency B	Severity C	Likelihood D	Risk* AxBxCxD	% Risk Reduction					
								equipment in range B																	
Using portable ladder for access to equipment	Falls	-	-	-	-	-	-	See <b>LS-JRA-0036</b> Use of Portable Ladder	-	-	-	-	-												
Elevated work 4 feet or more above a lower level	Falls	-	-	-	-	-	-	See <b>LS-JRA-0035</b> Elevated Work	-	-	-	-	-												
<b>Further Description of Controls Added to Reduce Risk:</b>																									
<b>*Risk:</b>	<b>0 to 20 Negligible</b>	<b>21 to 40 Acceptable</b>						<b>41 to 60 Moderate</b>						<b>61 to 80 Substantial</b>						<b>81 or greater Intolerable</b>					